



HXA021H

HXA024H

Accessories for x160**Indication contacts**

- 1 changeover switch (ON/OFF): indicates the position of the MCCB “open” or “close”.
- 1 changeover alarm contact: indicates MCCB tripped.

Coil connection

Connection capacity:
0.75 mm² flexible or rigid cables
The cable capacity of the terminals is 0.5 to 1.25 mm².

Shunt trip

Remote tripping of MCCBs
Operating voltage: 0.7 to 1.1 x U_n

Under voltage release

Enables tripping of MCCBs or moulded case switches when voltage level drop between 35 and 70% of U_n . Pick up voltage 0.85 x U_n

Direct rotary handle

- padlockable
- equipped with front cover and handle
- fixing without any additional screw.



HXA014H

Auxiliary Contacts

Description	Ref.
1 Changeover contact (On/Off) 250V AC / 3A 125V DC / 0.4A 1 NO+ 1NC	HXA021H
1 Changeover alarm contact 250 V AC / 3A 125 V DC / 0.4A NO + 1 NC	HXA024H
Low level contact (On/Off) 125V AC NO + 1 NC	HXA025H
Low Level alarm contact 125 V AC NO + 1 NC	HXA026H

Shunt Trips - SH

Description	Ref.
24V DC	HXA001H
48V DC	HXA002H
100-120V AC	HXA003H
200-240V AC	HXA004H
380-450V AC	HXA005H

Undervoltage Releases - UV

Description	Ref.
24V DC	HXA011H
100-120V AC	HXA013H
200-240V AC	HXA014H
380-450V AC	HXA015H

Delayed Undervoltage Releases - DUVR

Description	Ref.
24V DC	HXA051H
100-120V AC	HXA053H
200-240V AC	HXA054H
380-450V AC	HXA055H