



MAGPRO16 White MAGPRO16G Grey

Addressable 16 Zone Fire Panel



- 16 Zones
- Maximum 250 devices per loop
- Memory Log: 10,000 events
- Networkable up to 32 Panels
- Class change function
- 4 x 40 character LCD display
- Free programming software (On completion of training - UK)
- Micro USB port for PC connection
- Loop & battery calculator software included
- Certified to EN54-2/4

16 zone addressable fire alarm panel supplied with 1 loop. Expandable to 2 loops using MAGPRO16-L250. A maximum of 250 devices can be connected to each loop.

Inputs

Loops	1 expandable to 2
Devices Per Loop	250
Protocol	MAGPRO

Power

Mains Fail Consumption	125mA DC - 1 LOOP 213mA DC - 2 LOOP
Mains Supply	230V AC ± 10% / -15%
Max Loop Current	500mA DC
Backup	1x12V 18Ah

Outputs

2 Sounders	24v DC @ 500mA
4 Programmable Relays	24v DC @ 15A
3 Monitored Outputs	24v DC @ 100mA
3 Monitored Inputs	Volt free contacts

Environment

Working Temperature	-5°C TO +40°C
Storage	-10°C TO 60°C
Humidity	0 - 95%
Weight	4.2KG (Without Battery)
Dimensions	320 x 220 x 80mm



MAGPRO16-L250
Single Loop Expander for 250 Devices



MAGPRO-PROG Programming Tool
For more info see page 117